

认证说明

该证书只用于在网页浏览，证明赛尔特这个型号产品已获得认证。如需完整版

本，请用以下任意一种方式联系获得：

- 邮件：sales@SETfuse.com。
- 客服。
- 销售人员。

感谢您对赛尔特的支持！



Product Service

CERTIFICATE

No. B 107221 0012 Rev. 00

Holder of Certificate: XIAMEN SET ELECTRONICS CO LTD

No.8001 and No.8067 West Xiang'An Rd
Torch High-tech industrial District
361101 Xiamen
PEOPLE'S REPUBLIC OF CHINA

Certification Mark:



Product:

**Miniature fuses
(Miniature fuse-links for special applications)**

The product was tested on a voluntary basis and complies with the essential requirements. The certification mark shown above can be affixed on the product. It is not permitted to alter the certification mark in any way. In addition, the certification holder must not transfer the certificate to third parties. This certificate is valid until the listed date, unless it is cancelled earlier. All applicable requirements of the Testing, Certification, Validation and Verification Regulations of TÜV SÜD Group have to be complied. For details see: www.tuvsud.com/ps-cert

Test report no.: 64105243055201

Valid until: 2029-06-11

Date, 2024-06-12

(Martin Ma)

CERTIFICATE

No. B 107221 0012 Rev. 00

Model(s): **SCT1032**

Parameters:

| | |
|------------------------------|---|
| Rated voltage (U_N): | AC 350V/300V/250V/125V; DC 250V/125V/75V/63V/48V/32V |
| Rated current (I_N): | 100mA, 125mA, 160mA, 200mA, 250mA, 315mA, 400mA, 500mA, 630mA, 800mA, 1A, 1.25A, 1.6A, 2A, 2.5A, 3.15A, 4A, 5A, 6.3A, 8A, 10A, 12.5A, 15A |
| Rated breaking capacity: | See appended table 1 |
| Time/current characteristic: | 2.1 I_N : max. 120s (for rated current 15A); 2.0 I_N : max. 120s (for all rated current except 15A); 10 I_N : max. 0.1s (for all rated current) |
| Overvoltage: | 4000V |

Appended table 1: Rated breaking capacity

| Rated current (I_N) | Rated Breaking Capacity (@ U_N) | | | | | | | | | |
|-------------------------|------------------------------------|---------|---------|---------|---------|---------|--------|--------|--------|--------|
| | AC 350V | AC 300V | AC 250V | AC 125V | DC 250V | DC 125V | DC 75V | DC 63V | DC 48V | DC 32V |
| 100mA | 100A | 100A | 200A | 1000A | 50A | 1000A | 1000A | 1000A | 1000A | 1000A |
| 125mA | 100A | 100A | 200A | 1000A | 50A | 1000A | 1000A | 1000A | 1000A | 1000A |
| 160mA | 100A | 100A | 200A | 1000A | 50A | 1000A | 1000A | 1000A | 1000A | 1000A |
| 200mA | 100A | 100A | 200A | 1000A | 50A | 1000A | 1000A | 1000A | 1000A | 1000A |
| 250mA | 100A | 100A | 200A | 1000A | 50A | 1000A | 1000A | 1000A | 1000A | 1000A |
| 315mA | 50A | 50A | 200A | 1000A | 50A | 1000A | 1000A | 1000A | 1000A | 1000A |
| 400mA | 100A | 100A | 200A | 1000A | 50A | 1000A | 1000A | 1000A | 1000A | 1000A |
| 500mA | 100A | 100A | 200A | 1000A | 50A | 1000A | 1000A | 1000A | 1000A | 1000A |
| 630mA | 50A | 50A | 200A | 1000A | 50A | 1000A | 1000A | 1000A | 1000A | 1000A |
| 800mA | 50A | 50A | 200A | 1000A | 50A | 1000A | 1000A | 1000A | 1000A | 1000A |
| 1A | 50A | 50A | 200A | 1000A | 50A | 1000A | 1000A | 1000A | 1000A | 1000A |
| 1.25A | 50A | 50A | 200A | 1000A | 50A | 1000A | 1000A | 1000A | 1000A | 1000A |
| 1.6A | 50A | 50A | 200A | 1000A | 50A | 1000A | 1000A | 1000A | 1000A | 1000A |
| 2A | 50A | 50A | 200A | 1000A | 50A | 1000A | 1000A | 1000A | 1000A | 1000A |
| 2.5A | 100A | 100A | 100A | 1000A | 50A | 1000A | 1000A | 1000A | 1000A | 1000A |
| 3.15A | 100A | 100A | 200A | 1000A | 50A | 1000A | 1000A | 1000A | 1000A | 1000A |
| 4A | 100A | 100A | 200A | 1000A | 50A | 1000A | 1000A | 1000A | 1000A | 1000A |
| 5A | 50A | 50A | 100A | 1000A | 50A | 1000A | 1000A | 1000A | 1000A | 1000A |
| 6.3A | 100A | 100A | 100A | 1000A | -- | 1000A | 1000A | 1000A | 1000A | 1000A |
| 8A | 100A | 100A | 200A | 500A | -- | 1000A | 1000A | 1000A | 1000A | 1000A |
| 10A | 100A | 100A | 100A | 500A | -- | 1000A | 1000A | 1000A | 1000A | 1000A |
| 12.5A | 125A | 125A | 125A | 500A | -- | 1000A | 1000A | 1000A | 1000A | 1000A |
| 15A | 150A | 150A | 150A | 500A | -- | 1000A | 1000A | 1000A | 1000A | 1000A |

Tested according to: EN 60127-1:2006/A2:2015
EN 60127-7:2016